



TELETRONICS INTERNATIONAL

Feature

Designed for extending the range of 2.4 GHz wireless radio devices, the Smart-Amp is particularly effective when used with Direct Sequence or Frequency Hopping Spread Spectrum radio modems. The unit provides transmit power amplification and receives signal gain.

Full output power of 500mW is achieved with only 2.5mW input to the amplifier. Above 2.5 mW input, the smartamp attenuates the input signal power and maintains the output power typically at 500mW.

Substantial discounts available for OEMs and large volume purchases. Also available in 900MHz & 5.8GHz versions.

Contact sales office for details.

SmartAmp 2.4 GHz Series 500 mW Version



Specifications

Operating Range: 2400-2500 MHz
Operating Mode: TDD
Lightning Protection: Direct DC ground at antenna
DC Surge Protection: 600 Watts TVS @ 7.5 VDC

Mechanical & Environmental

Operating Temperature: -40 to +70 degree C
Power: 650mA @ 7.5VDC
Dimensions
Amplifier: 4.5" L X 3.0" W X 1.1"H
DC Injector: 3.5" L X 3.0" W X 1.2"H
Weight
Amplifier: 0.5 lb
DC injector: 0.4 lb
RF Connector: N, Female
Smart Function: Yes

Transmitter Amplifier

Transmit Gain: up to 22 dB
Transmit input power: 3 dBm (2 mW) min
23 dBm (200 mW) max
Transmit output power: max of 27dB (500mW)

Receiver Amplifier

Receive Gain: 12 dB typical
Frequency Response: +/- 1 dB
Noise Figure: 3.5 dB typical

Patents Pending

Copyright © 2001 by Teletronics International Inc. -
All rights reserved

Teletronics International Inc.

1803 Research Blvd. Suite 404 Rockville MD 20850

Phone: 301-309-8500 * Fax: 301-309-8851 Email: sales@teletronics.com * <http://www.teletronics.com/>